

# Digital Power Module (2-14S)

PMD05V08V

The PMD05V08V is designed to deliver a stable and regulated power supply from the battery to your Pixhawk® 5X and 6X. It also provides real-time battery voltage and current consumption data through a 6-pin cable. Equipped with an onboard switching regulator, it supports 5.2V/3A, 7.4V/2A or 12V/1.5A outputs, and is compatible with LiPo batteries up to 14S (HV).

The PMD05V08V comes fully assembled with XT60 connectors and is protected by heat-shrink tubing to enhance durability against physical damage.

Please note that this PMU is not intended to power servos; an external ESC or BEC should be used for servo power. The Molex compatible 2.00 mm connector supports up to 3.0A per contact.

## Specifications

<b>Scope of Application</b>	Used with Godwit G-A1, Pixhawk 5X/6X compatible
<b>Power Monitor Protocol</b>	I2C
<b>Input voltage</b>	2S-14S
<b>Continuous Current Rating</b>	60A*
<b>Burst Current Rating</b>	100A*
<b>Max Current Sensing</b>	327A
<b>Output Voltage</b>	Output 1 : 5.2V/3A Output 2 : 7.4V/2A or 12V/1.5A (Selectable)
<b>Connectors</b>	Input : XT60-F silicone wire (AWG 12) Output : XT60-M silicone wire (AWG 12)
<b>Dimensions</b>	35 x 28 x 10 mm (PCBA only) 35 x 240 x 10 mm (PCBA with XT60 cables)
<b>Weight</b>	40 g
<b>Accessories</b>	200mm Molex compatible 2.0mm 6P to 6P cable (AWG 24) 200mm Molex compatible 2.0mm 2P to 2P cable (AWG 22)

\*The PMD05V08V comes with XT60 connectors and AWG12 wires rated for 60A continuous current and 100A burst current (<60 seconds). If a higher current is needed, the plug type and wire size should be changed accordingly. See other models for reference.

## Pin Definition

